



The
Patent
Office

PCT/GB 00/02931



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

REC'D 12 SEP 2000

WIPO PCT

GB00/02931 4

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.


PRIORITY DOCUMENT

SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Signed

Dated

23 AUG 2000




THIS PAGE BLANK (USPTO)

02AUG99 E466166-1 003012
9917961.6 0.00 - 9917961.6

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)



The Patent Office

Cardiff Road
Newport
Gwent NP9 1RH

1. Your reference

P3075

2. Patent application number

(The Patent Office will fill in this part)

9917961.6

31 JUL 1999

3. Full name, address and postcode of the or of each applicant (underline all surnames)

HUNTLEIGH TECHNOLOGY PLC
GROUP IPR DEPARTMENT
310-312 DALLOW ROAD
LUTON
BEDFORDSHIRE
LU1 LTD
UNITED KINGDOM

506907003

Patents ADP number (if you know it)

If the applicant is a corporate body, give the country/state of its incorporation

4. Title of the invention

COMPRESSOR DRIVE

5. Name of your agent (if you have one)

"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)

AS ABOVE

Patents ADP number (if you know it)

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number

Country

Priority application number
(if you know it)

Date of filing
(day / month / year)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing
(day / month / year)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if:

- a) any applicant named in part 3 is not an inventor, or
- b) there is an inventor who is not named as an applicant, or
- c) any named applicant is a corporate body.

See note (d))

YES

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form —

Description 10

Claim(s) —

Abstract —

Drawing(s) 6

10. If you are also filing any of the following, state how many against each item.

Priority documents —

Translations of priority documents —

Statement of inventorship and right to grant of a patent (Patents Form 7/77) —

Request for preliminary examination and search (Patents Form 9/77) —

Request for substantive examination (Patents Form 10/77) —

Any other documents —
(please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

Sholimitzky 28.7.99

12. Name and daytime telephone number of person to contact in the United Kingdom

TRACEY LONG (01882) 745800

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

COMPRESSOR DRIVE

The present invention relates to a fluid flow control system and particularly a fluid flow control system for an electromagnetic pump which can provide any desired variable fluid flow rate.

Conventionally electromagnetic pumps operate from mains power and the compressors within the electromagnetic pumps operate directly from this single phase mains power which provides the compressor electrical drive input voltage and frequency. Therefore these compressors operate at constant fluid flow, and any fluid flow control depends merely on on/off control or on fluid loading conditions. The necessary fluid flow rates are obtained by the control and design of the fluid routing system.

Such compressors include linear or arcuate motion reciprocating actuators driven by electromagnetic drive means supplied by the mains power voltage and frequency. The electromagnetic drive means drive the actuators into reciprocating mechanical motion which is translated by diaphragms and valves into fluid flow from one or more compressor inputs to one or more compressor outputs.

This approach has a number of problems including the design of the compressor having to vary with the value of mains power voltage and frequency, complicating manufacture and driving up costs. Furthermore, flow control only by air routing compromises the compressors' life, the compressors having to be operated continually at maximum capacity with the consequence of maximum noise and vibration during use.

Furthermore, the performance of the compressors is largely dependent on the mechanical characteristics of its components, for example the diaphragm stiffness, the moving mass, and also the stiffness of the compressed air within the pump.

Any variation either between units of manufacture or within environmental operating conditions or through use will cause additional performance variation.

The aim of the present invention is to provide a fluid flow control system for an electromagnetic pump that is not dependent on the voltage and frequency of the mains power supply and provides the desired fluid flow with the optimum performance of the pump.

Accordingly, the present invention provides a fluid flow control system for an electromagnetic pump comprising electromagnetic drive means within a compressor, the control system supplying a pulse width modulated drive signal to the electromagnetic drive means so as to supply a predetermined pump flow rate, the drive signal generated from a dc voltage supply.

Preferably, the pulse width modulated drive signal comprises a train of variable mark space ratio pulses with defined repetition rates and amplitude. By varying the mark space ratio with time and appropriately defining its repetition rate and amplitude a drive signal compatible with the required flow rate can be obtained.

Preferably, the electromagnetic drive means includes stator(s) of magnetic material, excitation winding(s) for magnetically exciting the stator(s) and a movable magnetic member connected to the actuator of the compressor. An actuator deflection results in a corresponding deflection

of the attached diaphragm(s) and in flow of any fluid in contact with the diaphragm(s).

Preferably, the electromagnetic drive means in combination with diaphragms provides a conversion of
5 electrical energy to fluid flow.

Preferably, the pulse width modulated drive signal controls the instantaneous current within the excitation windings. This current by controlling actuator deflection amplitude and repetition rate controls fluid flow within
10 the compressor.

Preferably the mark-space ratio of the drive signal defines with time an approximate half sinewave waveform.

Preferably, the pulse width modulated drive signal is of substantially constant amplitude. Pulse width
15 modulated control from a dc power supply ensures the compressor is always operating with optimum efficiency for any application, the compressor performance being independent of mains power type or variations and allowing the possibility of using batteries to operate the pumps.
20 Therefore, the problems associated with existing fixed frequency mains voltage driven compressors and pumps are avoided.

According to a further aspect of the present invention, there is provided a fluid flow control system
25 for an electromagnetic pump comprising electromagnetic drive means within a compressor, the control system supplying a pulse width modulated low voltage drive signal of substantially fixed amplitude to the electromagnetic drive means to control the amplitude and repetition rate
30 of the current in the coils of the electromagnetic drive

means to drive the actuator in order to generate a desired flow rate output from the compressor.

Preferred embodiments of the present invention will now be described in detail by way of example only, with reference to the accompanying drawings of which:

Figure 1 shows a block diagram of the fluid flow control system according to the present invention;

Figure 2a shows the bipolar voltage drive signal;

Figure 2b shows the unipolar drive signal from the 10 mark space/repetition rate generator;

Figure 2c shows actuator current;

Figure 3 shows a block diagram of one embodiment of a control system of Figure 1 supplying fluid to a bladder; and

15 Figure 4 shows a block diagram of another embodiment of a control system of Figure 1 supplying fluid to a bladder;

Figure 5 shows a block diagram of a further embodiment of a control system of Figure 1 supplying fluid 20 to a bladder; and

Figure 6 shows a block diagram of a further embodiment of a control system of Figure 1 supplying fluid to a bladder.

Referring to the block diagram at Figure 1 there is 25 shown a controlled fluid flow system comprising a control system, fluid routing, a bladder system (7) and a compressor comprising one or more diaphragms (12) attached to an electromagnetic actuator (11).

The control system establishes a required current in 30 the compressor (6) coil or coils (10) at any instant in time. The coil current controls the position of the

actuator (11) which deflects the diaphragm(s) (12) appropriately thereby providing flow of any fluid in contact with the diaphragm(s) (12). Controlling the current in the coil(s) (10) controls the fluid flow from the compressor (6).

A command signal representing the required fluid flow is created in the command generator (1) and applied to the command processor (2) in conjunction with any feedback signal(s) (13) derived from the coil current sensor, actuator position sensor, bladder flow sensor and bladder pressure sensor. They provide signals representing instantaneous coil current, actuator displacement flow into or out of the bladder system (7) and bladder system (7) pressure.

The output of the command generator (1) and the feedback signals (13) are processed in the command processor (2) using a control algorithm which is representative of the pneumatic, mechanical and electrical characteristics of the compressor that is to be driven. From the control algorithm an appropriate drive signal is calculated, defined by mark-space ratio, repetition rate and amplitude parameters.

Drive signal amplitude is obtained via the amplitude controller (5) appropriately changing the power supply interface (14) within the power amplifier (4) to change the dc supply voltage of the 'H' bridge driver (15). The drive signal mark-space ratio and repetition rate are obtained by the mark-space and repetition rate generator operating on the appropriate parameter values. The generator provides a unipolar drive signal to the 'H'

bridge driver (15) which then provides a bipolar voltage drive signal to the compressor coil(s) (10).

This bipolar voltage drive signal (Figure 2a) across the compressor coils may be represented by repetition rate $1/A$, mark-space ratio B/A and amplitude switching between $+V$ and $-V$. V is a voltage closely approximating the supply voltage to the 'H' bridge driver (15). Typically V might be around 12 volts with a repetition rate of several kilohertz and mark-space ratio varying from below one per cent to above 99 per cent.

If for the purposes of obtaining appropriate compressor fluid flow an actuator current of period x is required (Figure 2c) then over a time period of x the generator (3) will provide mark-space ratio values approximating two half sinusoids (Figure 2b), each over a period of $x/2$ and with uniform repetition rate. This drive signal combined with the switching action of the 'H' bridge driver (Figure 2-a) will create a complete bipolar near sinusoidal actuator coil current with a period of x as required. Typically x will be ten to a hundred times greater than A requiring a drive signal repetition rate equally much higher than $1/x$.

The bipolar current in the compressor coil(s) enables the actuator to be displaced both positively and negatively with respect to its non-energised position. The actuator displacement results in the fluid pumping diaphragm(s) (12) being deflected to the required amount to provide the required flow rate of the fluid. The power amplifier (4) is supplied from mains power via a regulated or unregulated dc supply or from a dc battery.

It will be apparent to skilled practitioners of the art that for the invention except where indicated otherwise the command generator, mark-space and repetition rate generator, command processor, dc supply, power amplifier and amplitude controller can be implemented in any combination of analogue circuitry, digital circuitry or state machines including microprocessor systems.

It will also be apparent to skilled practitioners of the art that instead of diaphragms one can use other air displacement devices such as pistons, vanes, spirals, and that fluid flow out of as well as into the bladder system can be controlled.

Figure 3 shows a preferred embodiment of the invention where the characteristics of the compressor output fluid flow are known for varying loads, temperatures and pressures. In this case, a command signal representing the required fluid flow is created in the command generator (1) and applied to the command processor (2). The command processor (2) determines the repetition rate and mark-space ratio required from the mark-space and repetition rate generator (3). This results in a variable repetition rate and time varying mark-space ratio waveform representative of the current required in the compressor (6) coil or coils. The waveform is applied to the power amplifier (4) where it is controlled in amplitude by the amplitude controller (5), the amplitude being determined by the command processor (2). The output of the power amplifier (4) provides a voltage with the amplitude repetition rate and mark-space ratio controlled by the command processor. This voltage is applied to the compressor (6) coil or coils resulting in a known current,

therefore a known deflection of the compressor bellows and thus a known amount of fluid flow to the bladder system (7) by way of the fluid routing system (8). A dc power supply (9) is used.

5 Figure 4 shows the control of the fluid flow system as described in Figure 3 but applied to the control of the actuator position within the compressor by actuator position feedback. This control approach removes the effect of unknown variations within the electromagnetic
10 drive means between drive signal and resulting actuator deflection.

A command signal representing the required fluid flow is created in the command generator (1) and added to the actuator position sensor (10) signal in the command
15 processor (2) thus providing an error signal to ensure that the actuator position is achieved. This error signal from the command processor (2) determines the repetition rate and mark-space ratio required from the mark-space and repetition rate generator (3). This results in a variable
20 repetition rate and time varying mark-space ratio waveform representative of the current required in the compressor (6) coil or coils. This waveform is applied to the power amplifier (4) where it is controlled in amplitude by the amplitude controller (5), the amplitude being determined
25 by the command processor (2). The output of the power amplifier (4) provides a voltage with the amplitude repetition rate and mark-space ratio controlled by the command processor (2) and the actuator position sensor (10). This voltage is applied to the compressor (6) coil
30 or coils resulting in a known deflection of the compressor bellows and thus a known amount of fluid flow to the

bladder system (7) by way of the fluid routing system (8). A dc power supply (9) may also be used.

Figure 5 shows flow control based on the principle that the actual fluid flow into a bladder is monitored to maintain the required fluid flow.

A command signal representing the required fluid flow is created in the command generator (1) and added to the information from the flow sensor (10) in the command processor (2) thus providing an error signal to correct any error in the required flow. This error signal from the command processor (2) determines the repetition rate and mark-space ratio required from the mark-space and repetition rate generator (3). This results in a variable repetition rate and time varying mark-space ratio waveform representative of the current required in the compressor (6) coil or coils. This waveform is applied to the power amplifier (4) where it is controlled in amplitude by the amplitude controller (5), the amplitude being determined by the command processor (2). The output of the power amplifier (4) provides a voltage with the amplitude repetition rate and mark-space ratio controlled by the command processor (2) and the flow sensor (10). This voltage is applied to the compressor (6) coil or coils resulting in a deflection of the compressor bellows and thus an amount of fluid flow to the bladder system (7) by way of the fluid routing system (8). Any errors in the flow being detected by the flow sensor (10) and being used as a correction signal into the command processor (2). A dc power supply (9) is used.

Alternatively, instead of flow being monitored, the actual pressure in the bladder may be monitored as shown in Figure 6.

Referring to Figure 6, a command signal representing the required bladder pressure is created in the command generator (1) and added to the information from the pressure sensor (10) in the command processor (2) thus providing an error signal that can be used to correct any error in the required bladder system (7) pressure. This error signal from the command processor (2) determines the repetition rate and mark-space ratio required from the mark-space and repetition rate generator (3). This results in a variable repetition rate and time varying mark-space ratio waveform representative of the current required in the compressor (6) coil or coils. This waveform is applied to the power amplifier (4) where it is controlled in amplitude by the amplitude controller (5), the amplitude being determined by the command processor (2). The output of the power amplifier (4) provides a voltage with the amplitude repetition rate and mark-space ratio controlled by the command processor (2) and the pressure sensor (10). This voltage is applied to the compressor (6) coil or coils resulting in a deflection of the compressor bellows and thus an amount of fluid flow to the bladder system (7) by way of the fluid routing system (9). Any errors in the pressure detected by the pressure sensor (10) is then used as a correction signal into the command processor (2). A dc power supply is used (9).




FIGURE 1




FIGURE 2




FIGURE 3




FIGURE 4




FIGURE 5




FIGURE 6